

Ease of use

External manual bypass switches

External manual bypass switches for Protect B., C., C.R, 1. and 1.M series UPS units

The external manual bypass switch, an optional add-on for the Protect B., C., C.R, 1. and 1.M series of UPS systems, is used to bypass a UPS – for example, to carry out maintenance – without interrupting the supply of power to connected loads. Besides simple bypass operation, it features an additional setting to enable UPS testing. The switch is equipped with individually protected power connectors to supply power to loads directly.

The external manual bypass switch has three settings:

1. UPS mode:
Loads are supplied with power via the UPS.
2. Service mode:
Connected loads are powered directly from the mains supply. This setting also enables the UPS to be tested.
3. Bypass mode:
In this mode, loads are powered directly from the mains supply. The attached UPS is fully disconnected from the circuit and can be removed for maintenance or replacement.

Key features:

- Enclosures with a coordinated visual and technical design to match different UPS services
- Practical lasered and abrasion-resistant panel labeling
- High-quality can switch with leading and overlapping contacts
- Visual indication (green/yellow/red) of operating states (MBS 6000 only)
- Integrated power distribution unit; MBS 6000 additionally includes a terminal for supplying an external UPS
- Plug-and-go design for easy installation (MBS 2000/3000)
- Supplied complete with connection and installation kit
- Detailed user guide in several languages



Fig.: MBS 2000/3000, MBS 6000, MBS 24000



External manual bypass switches: Technical data

| | MBS 2000 | MBS 3000 | MBS 6000 | MBS 24000 |
|---------------------------------|-----------------------------------------|------------------------------------------|--------------------------------------------------------------------------------------------------------------------|--------------------------|
| Compatibility | B.750-B.2000 C.1000 (R) / C.2000 (R) | B.3000 / C.3000 (R) | C.6000 (R) | C.10000 / 1. / 1.M |
| Nominal input voltage Frequency | 230 Vac, 50/60 Hz | 230 Vac, 50/60 Hz | 230 Vac, 50/60 Hz | 230 Vac, 50/60 Hz |
| Nominal current | 10 A | 16 A | 32 A | 32 A bis 125 A |
| No. of output connections | 4 x I/C 320 (C 13) | 4 x I/C 320 (C 13) 1 x I/C 320 (C 19) | 8 x I/C 320 (C 13), protected in pairs by 5 x 20mm micro fuse (I. 10 A), plus unprotected terminal output | 16 x terminals |
| Enclosure color | Blackline | Blackline | Blackline | Blackline |
| Dimensions (H x W x D) | | | | |
| Tower mode | 85 mm x 215 mm x 200 mm | | 85 mm (2 U) x 483 mm (19") x 350 mm | 600 mm x 390 mm x 350 mm |
| 19" Rack mode | 80 mm (2 U) x 483 mm (19") x 200 mm | | | |
| AEG part number | 600 000 3039 | 600 000 3040 | 600 000 5205 | 100 000 2021 |

AEG is a registered trademark used under license from AB Electrolux • Specifications are subject to change without notice • 03/2009

Authorized distributor in Slovakia:

Rhea elektro s.r.o.
Elektrárenská 1/ 12440, 831 04 Bratislava
Tel.: +421 2 49101914, -18
E-mail: info@rhea-elektro.sk
www.rhea-elektro.sk

PERFECT IN FORM AND FUNCTION

AEG